

Headlight replacement on Jeep Wrangler JL/Gladiator

When upgrading headlights on a Jeep Wrangler JL/Gladiator, you will need one set of 7" headlights (JP-70xxx) and the JP-JLB7 mounting brackets. Included with the JP-JLB7 will be one set of H4 to OE wiring adapters that will be used. The H4 to H13 wiring adapters that are included with the 7" headlights are not applicable to this application, and will not be used.

Unlike the Jeep Wrangler JK, the electrical system in these newer models do not need the addition of a canbus decoder (JP-H4H13DE) to complete the installation. In fact, adding the canbus decoder in these applications can cause the headlights to flash, work intermittently, or not at all. These undesired results may occur with or without any dash notification of the issue. If you are experiencing these problems on a Jeep Wrangler JL/ Gladiator, please check for the installation of canbus decoders. Removing the decoders will return the lights to normal functionality.

JP-JLB7



JP-H4H13DE

